



KTH Matematik

Homework 1
Mathematical Systems Theory, SF2832
Spring 2011

You may use $\min(5, (\text{your score})/5)$ as bonus credit on the exam.

1. Solve the following linear state equations

(a) $\dot{x}(t) = \begin{bmatrix} -1 & 0 & 0 \\ 0 & \lambda & -\sigma \\ 0 & \sigma & \lambda \end{bmatrix} x(t), x(0) = \begin{bmatrix} 1 \\ 1 \\ 0 \end{bmatrix}$, where $\lambda \neq 0, \sigma > 0$ (2p)

(b) $\dot{x}(t) = \frac{t}{1+t^2} x(t), x(t_0) = 1$ (2p)

(c) Let

$$A(t) = \begin{bmatrix} a_{11}(t) & a_{12}(t) \\ a_{21}(t) & a_{22}(t) \end{bmatrix}.$$

Show

$$\det \Phi(t, t_0) = e^{\int_{t_0}^t (a_{11}(s) + a_{22}(s)) ds}.$$

..... (3p)

2. Determine when the system is reachable

(a)

$$\dot{x}(t) = \begin{bmatrix} \frac{t}{1+t^2} & 0 & 0 \\ 0 & \lambda_1 & 0 \\ 0 & 0 & \lambda_2 \end{bmatrix} x(t) + \begin{bmatrix} 1 \\ 1 \\ 1 \end{bmatrix} u(t),$$

where λ_1, λ_2 are real numbers. (3p)

(b)

$$\dot{x} = \begin{bmatrix} A_1 & A_2 \\ A_3 & A_4 \end{bmatrix} x + \begin{bmatrix} B_1 \\ 0 \end{bmatrix} u(t)$$

where B_1 has full row rank and

$$A_3 = \begin{bmatrix} 1 \\ 1 \end{bmatrix} \quad A_4 = \begin{bmatrix} a_1 & 0 \\ 0 & a_2 \end{bmatrix}$$

and a_1, a_2 are real numbers. (3p)

3. Consider

$$\dot{x}(t) = Ax(t)$$

$$y(t) = cx(t)$$

where

$$A = \begin{bmatrix} a_{11} & a_{12} \\ a_{21} & a_{22} \end{bmatrix}, \quad c = [c_1 \quad c_2].$$

- (a) Show that if the two eigenvalues of A are distinctive, then we can always find a c such that (c, A) is observable. (3p)
 - (b) Show that if the imaginary part of the eigenvalues is none-zero, then (c, A) is observable for all $c \neq 0$ (2p)
 - (c) Now let $a_{11} = a_{22} = 0$, $a_{12} = -a_{21} = \sigma > 0$ and suppose we can only measure $y(t)$ where $c \neq 0$ at $t = 0, T, 2T, \dots$. What are the sampling periods T we should avoid if we want to reconstruct the initial state x_0 from the measurements? (2p)
4. (a) A solution $x(t)$ is called periodic if $x(t + T) = x(t) \forall t$ for some $T > 0$. A periodic solution is called non-degenerated if $x(t)$ is not constant. Show that linear time-invariant systems

$$\dot{x} = Ax$$

can never have just one non-degenerated periodic solution. What further conclusion can you draw from your proof? (3p)

- (b) Verify that $X(t) = e^{At} X_0 e^{Bt}$ is the solution to the matrix differential equation

$$\dot{X} = AX + XB, \quad X(0) = X_0.$$

..... (2p)