



KTH Matematik

**Homework 2**  
**Mathematical Systems Theory, SF2832**  
**Fall 2014**

**You may use min(5,(your score)/5) as bonus credit on the exam.**

1. Consider the pair  $(C, A)$ , where

$$A = \begin{bmatrix} a_1 & a_2 \\ 1 & 0 \end{bmatrix}$$
$$C = [0 \quad 1].$$

For what  $a_1$  and  $a_2$  the Lyapunov equation  $A^T P + PA + C^T C = 0$  has

- (a) a positive definite solution? ..... (1p)
- (b) a negative definite solution ( $-P$  is positive definite)? ..... (1p)
- (c) a solution that is neither positive nor negative definite? Where are the eigenvalues of  $A$  located in this case? ..... (2p)

2. You will in this problem derive and investigate a number of realizations for the transfer function

$$R(s) = \begin{bmatrix} \frac{\gamma}{s+1} & \frac{1}{s+1} \\ \frac{1}{(s+1)^2} & \frac{1}{(s+1)^2} \end{bmatrix},$$

where  $\gamma > 0$  is a constant.

- (a) Determine the standard reachable realization of  $R(s)$ . ..... (1p)
- (b) What is the McMillan degree of  $R(s)$ ? ..... (2p)
- (c) Find a minimal realization of  $R(s)$  for  $\gamma = 1$ . ..... (3p)

3. (a) Given the matrix

$$A = \begin{bmatrix} 0 & 1 & 0 & \cdots & 0 \\ 0 & 0 & 1 & \cdots & 0 \\ \vdots & \vdots & \vdots & \ddots & \vdots \\ 0 & 0 & 0 & \cdots & 1 \\ -a_1 & -a_2 & -a_3 & \cdots & -a_n \end{bmatrix},$$

Suppose all the eigenvalues of  $A$  are real. Show that  $A$  is diagonalizable by a linear transformation  $T$  if and only if all the eigenvalues of  $A$  are distinct. (3p)

(b) Consider a controllable and observable system

$$\begin{aligned} \dot{x} &= Ax + bu \\ y &= cx, \end{aligned}$$

where,  $x \in R^n$ ,  $u \in R$ ,  $y \in R$ . We say the system has relative degree  $r$  if  $cb = 0, \dots, cA^{r-2}b = 0$ , and  $cA^{r-1}b \neq 0$ . Show we can find  $u = kx = \sum_{i=1}^n k_i x_i$  such that  $(c, A + bk)$  is not observable if and only if  $r < n$ . ..... (3p)

(c) Consider

$$\begin{aligned} \dot{x}_1 &= x_2 \\ \dot{x}_2 &= u, \end{aligned}$$

one can use high gain control  $u = -2k^2x_1 - 3kx_2$ ,  $k > 0$  to place the poles to  $-k, -2k$ . To see a drawback of having too high gain, show that for the closed-loop system if  $|x_1(0)| \neq 0$

$$\lim_{k \rightarrow \infty} \max_{t \geq 0} |x(t)| = \infty.$$

..... (3p)

4. Consider the inverted pendulum




Figure 1: Inverted pendulum on a cart.

The following equation describes the motion of the pendulum around the equilibrium  $\theta = 0$ :

If  $|\theta(t)| < \frac{\pi}{2}$ :

$$L\ddot{\theta} - g \sin(\theta) + \ddot{x} \cos(\theta) = 0, \tag{1}$$

If  $|\theta(t)| = \frac{\pi}{2}$ :

$$\dot{\theta} = 0, \ddot{\theta} = 0. \tag{2}$$

(2) indicates that once the pendulum falls on the cart, it remains in that position. Assume  $L = 1$ , and let  $x_1 = \theta$ ,  $x_2 = \dot{\theta}$ ,  $u = \ddot{x}$ , we can linearize (1) as

$$\begin{aligned}\dot{x}_1 &= x_2 \\ \dot{x}_2 &= gx_1 - u\end{aligned}\tag{3}$$

- (a) Design  $u = gx_1 + k_1x_1 + k_2x_2$ , where  $k_1 + k_2 \leq 30$ , such that
- (3) is asymptotically stable, and
  - use the nonlinear model (1) AND (2) and Matlab to find out what is the maximum  $|\theta(0)|$  while  $\dot{\theta}(0) = 0$  you can swing up. Give this maximum value with an accuracy of  $\pm 0.1$  degree and attach the simulation plot as evidence. .... (3p)

**Note:** If the best value is obtained by not more than two students, then the winner(s) will receive **two extra bonus credits** for the exam, provided that the winning control is allowed to be published on the course web.

- (b) Now let  $y = x_1$ . Design an observer based on (3) and repeat the simulation. Attach a plot to show what is the maximum angle now. .... (3p)